

IR Control Codes

<u>Function</u>	<u>Hex Code</u>
1. Power On	5ca338c7
2. Off (Standby)	5ca3b847
3. Menu	5ca3f807
4. Up	5ca308f7
5. Down	5ca38877
6. Left	5ca3c837
7. Right	5ca348b7
8. Select/Enter	5ca328d7
9. Mute	5ca3a857
10. Brightness_Up	5ca318e7
11. Brightness_Down	5ca39867
12. Contrast_Up	5ca358a7
13. Contrast_Down	5ca3d827
14. Red Button - step through aspect ratios	5ca37887
15. Info window	5ca3847b
16. PIP	5ca3a45b
17. PIP_Swap	5ca3649b
18. 0	5ca300ff
19. 1	5ca3807f
20. 2	5ca340bf
21. 3	5ca3c03f

<u>Function</u>	<u>Hex Code</u>
22. 4	5ca320df
23. 5	5ca3a05f
24. 6	5ca3609f
25. 7	5ca3e01f
26. 8	5ca310ef
27. 9	5ca3906f
28. Input Select Up	5ca36897
29. Input Select Down	5ca3e817
30. Picture format: Normal	5ca330cf
31. Picture format: Full	5ca331ce
32. Picture format: Crop	5ca332cd
33. Picture format: Anamorphic	5ca333cc
34. Picture format: Flex Wide	5ca334cd
35. Picture format: 2.35:1	5ca335ca
36. Contrast Enhance: Normal	5ca350af
37. Contrast Enhance: Cinema	5ca351ae
38. Contrast Enhance: Video	5ca352ad
39. Contrast Enhance: Vivid	5ca353ac
40. Contrast Enhance: Dark Scene	5ca354ab
41. Contrast Enhance: Bright Scene	5ca355aa

All codes are RC5 style at 38KHz.

Headquarters
Calibre UK Ltd
Cornwall House, Cornwall Terrace
Bradford, West Yorkshire
BD8 7JS, England

Telephone + 44 (0)1274 394125
Fax + 44 (0)1274 730960
Email vantage@calibreuk.com
Web-site www.calibreuk.com